

SB100-011G-4-PV Solar Water Pump Controller

SB100-011G-4-PV

11 kW SB100 Solar Pumping VFD

SB100 solar water pump controller with MPPT tracking efficiency up to 99%, automatic start and sleep, PV over-voltage and over-current protection, automatic over-temperature derating, optional GPRS app monitoring and an optional IP54 cabinet.



Rated Electrical Data

Rated values from the SB100 data sheet.

Rated Output Power	11 kW
Rated Input Current	32 A
Rated Output Current	25 A
Maximum DC Input Current	40 A

Recommended Solar Modules

Recommended module power and string configuration for modules with 37 ± 1 V or 45 ± 1 V open-circuit voltage.

37 V Module Power	250 Wp
37 V Modules per String	18
37 V Parallel Strings	3
45 V Module Power	300 Wp
45 V Modules per String	15
45 V Parallel Strings	3

Installation Dimensions

Controller dimensions and installation-hole diameter in millimetres.

W1	170.5 mm
W2	152 mm
H1	320 mm
H2	305 mm
D1	196.3 mm
D2	115 mm
Installation Hole Diameter	6 mm

Controller Configuration

Model code and controller configuration.

Model Configuration Code	4
---------------------------------	---

Features and Operating Notes

Shared SB100 features and configuration notes.

Maximum MPPT Tracking Efficiency	99 %
Protection Functions	PV over-voltage protection; over-current protection; automatic derating against over-temperature.
Remote Monitoring	Optional GPRS module for remote controller monitoring through the app.
Automatic Start and Sleep	Yes
Cabinet Option	Optional cabinet product for IP54 protection level.
AC and DC Input Note	Simultaneous AC and DC access requires customization.
Pump Compatibility Note	Synchronous water pump configurations require customization. The factory default is DC input controlling an asynchronous water pump.

Solar Water Pumping System Diagram



SB100 Solar Water Pump Controller Wiring Diagram

